

type number	(mm)	leught (mm)	weight (kg/m)	strengh class	max. tensile load (kN)	8
ZT 6_ZNCR	M6	2000	0,17	4.8	2,56	% %
ZT 8_ZNCR	M8	2000	0,31	4.8	4,69	& &
ZT 8_ZNC1	M8	1000	0,31	4.8	4,69	& &
ZT 8_ZNC3	M8	3000	0,31	4.8	4,69	* *
ZT 10_ZNCR	M10	2000	0,46	4.8	7,47	% %
ZT 10_ZNC3	M10	3000	0,46	4.8	7,47	% %
ZT 10_GMT	M10	1000	0,46	8.8	19,92	& &
ZT 12_ZNCR	M12	2000	0,70	4.8	10,89	A A



product description: The threaded rod is used to suspend the cable route under the ceiling or

as part of the anchorage for fixing structures or their parts to the

underlying material.

The stated maximum load applies to the load at rest.

DIN 975/976

surface finish: ZNC... / ZNCR - bichromatic galvanised

GMT - non electrolytic plating, aluminum-zinc-layer 5-15 μm (equivalent

Hot Dip Galvanized)

klasifikace **%**: ČSN 73 0895 P 90-R

DIN 4102-12 E 90 STN 92 0205 PS 90

Fire classification depends on the specific conditions of the cable tray, detailed in the catalog Systems with maintained functionality in fire.

products are approved for standard constructions

products are approved for non-standard constructions

storage: ČSN EN 60721-3-1





Risk of injury from cutting

Although the cable trays are produced with maximum effort to minimize sharper edges, it is necessary to wear protective gloves to carry, grip and work with cable elements.

Risk of system collapse

It is essential to strictly adhere to the maximum load limits for individual cable support systems and ensure proper installation according to the installation manual. The load capacity charts for each system are provided in the manufacturer's catalog, available in printed form or on the manufacturer's website. The specified load limits do not account for any additional loads, such as snow, wind, or seismic forces.

Electricity injury

As individual components of cable management systems are made of electrical conductive material, it is essential not to work with a system near live electrical parts. Infringement of the safety regulations may cause serious injury of health or death.

Safe Use

Under normal and foreseeable conditions of use, there are no risks to consumers, provided that proper installation and usage are carried out in accordance with the installation manual.

recycling codes:

